

manual

Fast charger / PD 65 W

Item: 22950, 22951

EN

NO

SV

www.linocell.com
Box 50435 Malmö
Sweden
2023-07-12



LINOCELL®
PREMIUM

Specifications

Input: 100–240 V (AC), 50/60 Hz, 2.0 A max.

Total output all ports: Up to 65 W

Output USB-C 1/2: PD 3.0 up to 65 W each

Output USB-A: QC up to 30 W

Size: 41x38x84 mm

Weight: 114 g

Output, using one port at the time:

Output USB-C,
port 1/2: PD 5.0 V/9.0 V/12.0 V/15.0 V=3.0 A,
20.0 V=3.25 A (65.0 W Max.)
PPS: 3.3–20.0 V=3.0 A (60.0 W Max.)

Output USB-A: QC 4.5 V=5.0 A, 5.0 V=4.5 A, 9.0 V=3.0 A,
12.0 V=2.5 A, 20.0 V=1.5 A (30.0 W Max.)

Output, using several ports:

USB-C, port 1 + 2: 45.0 W+20.0 W (65.0 W Max.)

USB-C1: PD 5.0 V/9.0 V/12.0 V/15.0 V
=3.0 A, 20.0 V=2.25 A (45.0 W Max.)
PPS: 3.3–16.0 V=3.0 A (45.0 W Max.)

USB-C2: 5.0 V=3.0 A/9.0 V=2.2 A,
12.0 V=1.67 A (20.0 W Max.)
PPS: 3.3–11.0 V=2.0 A (20.0 W Max.)

USB-C port 1 +
USB-A port: 45.0 W+18.0 W (63.0 W Max.)

USB-C1: PD 5.0 V/9.0 V/12.0 V/15.0 V
=3.0 A, 20.0 V=2.25 A (45.0 W Max.)
PPS: 3.3–16.0 V=3.0 A (45.0 W Max.)

USB-A: QC 5.0 V=3.0 A, 9.0 V=2.0 A,
12.0 V=1.5A (18.0 W Max.)

USB-C port 2 + USB-A	5.0 V→1.5 A+5.0 V→1.5 A (15.0 W Max. Shared)
All ports:	45.0 W+15.0 W (60.0 W max.) USB-C1: PD 5.0 V/9.0 V/12.0 V/15.0 V→3.0 A, 20.0 V→2.25 A (45.0 W Max.) PPS: 3.3–16.0 V→3.0 A (45.0 W Max.) USB-C2+USB-A: 5.0 V→3.0 A (15.0 W Max. Shared)

Average active efficiency (%):	≥ 86.0 %
Efficiency at low load (10 %):	78.84 %
No-load power consumption (W):	≤ 0.3 W

Safety information

Always grab the adapter when unplugging it from the wall socket. The power connector plug is used as the main way to turn off the charger, therefore the power connector must be easy to reach during use. This charger is only intended for household use and may only be used indoors. Children should be supervised to ensure that they do not play with the charger. Do not expose the charger to high temperatures, moisture, or strong and direct sunlight.

Spesifikasjoner

Spenning inn:	100–240 V (AC), 50/60 Hz, maks. 2,0 A
Utgangseffekt:	Opptil 65 W
Utgang USB-C 1/2:	PD 3.0 opptil 65 W hver
Utgang USB-A:	QC opptil 30 W
Mål:	41x38x84 mm
Vekt:	114 g

Utgang, én port om gangen:

Utgang USB-C, port 1/2:	PD 5,0 V/9,0 V/12,0 V/15,0 V→3,0 A; 20,0 V→3,25 A (maks. 65,0 W) PPS: 3,3–20,0 V→3,0 A (maks. 60,0 W)
Utgang USB-A:	QC 4,5 V→5,0 A; 5,0 V→4,5 A, 9,0 V→3,0 A; 12,0 V→2,5 A; 20,0 V→1,5 A (maks. 30,0 W)

Utgang ved bruk av flere porter:

USB-C, port 1 + 2:	45,0 W+20,0 W (maks. 65,0 W) USB-C1: PD 5,0 V/9,0 V/12,0 V/15,0 V→3,0 A; 20,0 V→2,25 A (maks. 45,0 W) PPS: 3,3–16,0 V→3,0 A (maks. 45,0 W) USB-C2: 5,0 V→3,0 A/9,0 V→2,2 A; 12,0 V→1,67 A (maks. 20,0 W) PPS: 3,3–11,0 V→2,0 A (maks. 20 W)
--------------------	--

USB-C port 1 + USB-A port:	45,0 W+18,0 W (maks. 63,0 W) USB-C1: PD 5,0 V/9,0 V/12,0 V/15,0 V →3,0 A; 20,0 V→2,25 A (maks. 45,0 W) PPS: 3,3–16,0 V→3,0 A (maks. 45,0 W) USB-A: QC 5,0 V→3,0 A, 9,0 V→2,0 A; 12,0 V→1,5 A (maks. 18,0 W)
USB-C port 2 + USB-A	5,0 V→1,5 A + 5,0 V→1,5 A (maks. 15,0 W delt)
Alle porter:	45,0 W+15,0 W (maks. 60,0 W) USB-C1: PD 5,0 V/9,0 V/12,0 V/15,0 V →3,0 A; 20,0 V→2,25 A (maks. 45,0 W) PPS: 3,3–16,0 V→3,0 A (maks. 45,0 W) USB-C2+USB-A: 5,0 V→3,0 A (maks. 15,0 W delt)
Energieffektivitet- aktiv (%):	≥ 86,0 %
Energieffektivitet - lav belastning (10%):	78,84 %
Strømforbruk - ingen belastning (W):	≤ 0,3 W

Sikkerhetsinformasjon

Alltid ta tak i adaptøren når du kobler den fra stikkkontakten. Strømkontakten brukes som hovedmåte for å slå av laderen, derfor må strømkontakten være lett tilgjengelig under bruk. Denne laderen er kun beregnet for husholdningsbruk og skal kun brukes innendørs. Barn bør være under oppsyn for å sikre at de ikke leker med laderen. Ikke utsett laderen for høye temperaturer, fuktighet eller sterkt direkte sollys.

Specifikationer

Spänning in:	100–240 V (AC), 50/60 Hz, max. 2,0 A
Utgångseffekt:	Upp till 65 W
Utgång USB-C 1/2:	PD 3,0 V upp till 65 W var
Utgång USB-A:	QC upp till 30 W
Storlek:	41x38x84 mm
Vikt:	114 g
Utgång, en port i taget:	
Utgång USB-C, port 1/2:	PD 5,0 V/9,0 V/12,0 V/15,0 V→3,0 A; 20,0 V→3,25 A (max. 65,0 W) PPS: 3,3–20,0 V→3,0 A (max. 60,0 W)
Utgång USB-A:	QC 4,5 V→5,0 A; 5,0 V→4,5 A, 9,0 V→3,0 A; 12,0 V→2,5 A; 20,0 V→1,5 A (maks. 30,0 W)

Utgång vid användning av flera portar:

USB-C, port 1 + 2:	45,0 W+20,0 W (max. 65,0 W) USB-C1: PD 5,0 V/9,0 V/12,0 V/15,0 V →3,0 A; 20,0 V→2,25 A (max. 45,0 W) PPS: 3,3–16,0 V→3,0 A (max. 45,0 W) USB-C2: 5,0 V→3,0 A; 9,0 V→2,2 A; 12,0 V→1,67 A (max. 20 W) PPS: 3,3–11,0 V→2,0 A (max. 20,0 W)
--------------------	--

USB-C port 1 + USB-A port:	45,0 W+18,0 W (max. 63,0 W) USB-C1: PD 5,0 V/9,0 V/12,0 V/15,0 V =3,0 A; 20,0 V=2,25 A (max. 45,0 W) PPS: 3,3–16,0 V=3,0 A (max. 45,0 W) USB-A: QC 5,0 V=3,0 A; 9,0 V=2,0 A; 12,0 V=1,5 A (max. 18,0 W)
USB-C port 2 + USB-A port	5,0 V=1,5 A + 5,0 V=1,5 A (max. 15,0 W delat)
Alla portar:	45,0 W+15,0 W (max. 60,0 W) USB-C1: PD 5,0 V/9,0 V/12,0 V/15,0 V =3,0 A; 20,0 V=2,25 A (max. 45,0 W) PPS: 3,3–16,0 V=3,0 A (max. 45,0 W) USB-C2+USB-A: 5,0 V=3,0 A (max. 15,0 W delat)
Genomsnittlig verknings- grad i aktivt läge (%):	≥ 86,0 %
Verkningsgrad vid låg last (10 %):	78,84 %
Elförbrukning vid noll-last (W):	≤ 0,3 W

Säkerhetsinformation

Ta alltid tag i adaptern när du kopplar ur den från vägguttaget. Strömkontakten används som huvudsakliga sättet att stänga av laddaren, därför måste strömkontakten sitta lättillgängligt under användning. Denna laddare är endast avsedd för hushållsbruk och får endast användas inomhus. Barn bör hållas under uppsikt för att säkerställa att de inte leker med laddaren. Utsätt inte laddaren för höga temperaturer eller luftfuktighet, eller starkt direkt solljus.