



Universal Wireless Remote Controller User Manual



Many thanks for purchasing our product! This is a portable Wireless control, used for mobile phone, MID, TV box, smart TV, PC and so on. It can be used as gamepad, wireless mouse, music control, e-book page, PPT presentation etc. and support iOS, Android, Windows and so on.

Important Note: Products are subject to change without any notice. And this product has applied for patents, counterfeiting is not permitted.

Operating instructions:

1. Power On: Press **START/U** button until LED is on (about 2 seconds).
Force iOS mode boot: Power on automatically according to the system to enter the Apple iOS mode or Android mode. If the Apple iOS phone can't be detected normally, please under power off state, press **Ⓢ** key first, then press **START/U** at same time until red LED light is on, the device turn on successfully. (**Ⓢ** and **START/U** return to auto mode)
2. Power Off: Press **START/U** button until LED is off (about 5 seconds). Note: If no connecting with Bluetooth device after 5mins, system will power off automatically; after connecting with Bluetooth device, if no any operation, system will power off after 60mins.
3. Pair and connect: after power on, LED indicator will flash, the device will enter into the Bluetooth pair mode automatically to find the address and name of this device (MOCUTE-032_xx), click then can connect. Pair and connect successfully, LED indicator will turn off. Next power on, it can connect and match the last Bluetooth device. Under turn off state, press **START/U** (over 8 seconds), LED will flash, then go to pair mode again, and can't connect last paired device automatically.
4. KEY Mode: Turn switch on side to KEY (there is "KEY" on the back), The device operation is one-hand vertical operation. (as shown to the right)
- 4.1 Music operation:
After connecting with Bluetooth, open mobile's music player (like Samsung's player), click play, then can use this device to operate, like music play, pause, changing songs and so on. There are some



02

difference due to different software and system, like: **Ⓢ** key is for mute under iOS, but for camera under Android.

4.2 Shutter operation

For iOS mobile, press **Ⓢ** key to shutter; for Android Samsung mobile, then press **Ⓢ** key to shutter, Volume key to adjust focus; for other Android mobile, please enter camera setup first, then set volume key to shutter or scan barcode to download Zhuzilin camera software.

4.3 Mouse operation (just for Android)

Press **START/U** and **Ⓢ** at same time, then joystick can change to mouse function, **START/U** is for mouse confirm key. Press **START/U** and **Ⓢ** at same time, then can switch to music mode. If need mouse function in default when power on, please press button **START/U** and **Ⓢ** at same time to boot.

MENU function: press **Ⓢ** and **Ⓢ** at same time, then change to MENU.

4.4 E-Book flip function

In iReader: use Volume +/- to turn page up/down; In Kindle, use Game mode to turn page.

5. GAME function: Turn side switch to Game side (there is "GAME" on back), now device is operated by two-hands horizontal.

5.1 Game function on Android

In Menu, if joystick can move cursor, Key **Ⓢ** is confirmation button, Key **Ⓢ** is returning button, then means your mobile system can support international standard gamepad, just download game and play directly (If can't operate, then refer to part 6, Android MTK mobile operation)

Game Download: use QR code software to scan QR code on the packing (or enter into website: <http://www.migamepad.com>) to enter



03

into MIGAMEPAD download center, then you can download MIGAMEPAD game application or third party's game application. MIGAMEPAD Game center have all gamepad games, and support NES/GB/GBC/SFC/SMD/GBA/N64/MAME/PSX games. Users can also download simulator BIN files to Games file folder in mobile, then can use MIGAMEPAD software to open the game files, like many famous games: Super Mario, Metal Slug, Sangokushi and so on.

Android games usually have gamepad type, download this kind of games, just connect with Bluetooth then can operate with gamepad directly (please note, turn side switch to "Game"), this kind of games are like: Eternity Warriors 2, FIFA 15 and so on. (Some games maybe need set to use gamepad control when playing)

senior game combination key:

SELECT= **START/U** + **Ⓢ** L1= **START/U** + **Ⓢ** R1= **START/U** + **Ⓢ**
right joystick= left joystick + **START/U** L2= **START/U** + **Ⓢ** + **Ⓢ** R2= **START/U** + **Ⓢ**

5.2 iOS game

Game download: Enter into iOS APP store or other Apple store, search "icade", then you can find games of iCade which support gamepad, download and install then ok, like Akane Lite, Brotherhood, TTR Premium and so on.

Before play games, please set keyboard input mode to English input and can input English letters then ok. Next, please connect with Bluetooth and enter games then can play (Some games maybe need set to use iCade when playing)

Combination keys: SELECT= **START/U** + **Ⓢ**, L1= **START/U** + **Ⓢ**, R1= **START/U** + **Ⓢ**
Note: After the handle connection soft keyboard can't appear, Toggle the toggle switch can tune out of the soft keyboard.

6. Android MTK mobile operation

Like Redmi 3G version, Huawei Honor3X, CoolPAD, Zhongxing, these old style mobiles use MTK CPU, due to MTK bad compatibility, they can't support international standard gamepad agreement. So if by standard Android connection method, unusual problems will happen. We preset MTK mode to support MIGAMEPAD games.

04

6.1 MTK Power on mode: under power off state, press key **Ⓢ** first, then press **START/U** at same time until red LED light is on, the device turn on successfully. Next time, press key **START** then default to MTK mode. If want to shift to standard Android mode, press key **Ⓢ**, and **START/U**, then ok.

6.2 Function instruction on MTK mode Music, mouse and shutter are same with standard Android, just game mode is different. MTK mode can support MIGAMEPAD simulation directly, but can't support standard Android APK games.

7. Charge: Our product is with inner rechargeable lithium battery, when power is low, charging LED will flash (standard mode is red color, MTK mode is blue color), please insert 5V USB port to charge, then charging LED will be on. And when power is full, charging LED will be off.

Notes:

1. When accident cause not boot or unable to shutdown, please use needle to press Reset button on back
2. If already paired, but can't connect, please cancel the pair and boot the device and connect again.

Product Specifications

Item	SPEC
SIZE	73mmx31mmx13mm
Wireless Protocol	Wireless 3.0 Compliant
Wireless Distance	2-10 Meters
OS	Android/iOS/PC
CPU	ARM968E-S Core

05

Battery	Rechargeable lithium battery
Working time	>10 hours
Working current	0.5-8mA
Standby current	0.5-1mA
Recharging current	5V <200mA
Shutdown current	<20uA